


SPI 280
Page 2 of 2
July 5, 1957

STATOR CAM P/N 3719260 SHOWING
POSITION OF ROLLER AND SPRING

OPEN ENDS OF SPRING
TOWARD GROUND SLEEVE



SPI 292
Page 1 of 1
August 5, 1957

SUBJECT: RELEASE OF NEW CONVERTER CHARGING
PUMP AND NEW CONVERTER PUMP HUB

EQUIPMENT AFFECTED: TC-300 CONVERTER - ALL MODELS

EFFECTIVE SERIAL NUMBER: S/N 19085 - JUNE 6, 1957

As a product improvement, a new converter charging pump and a new converter pump hub have been released to the TC-300 converters. The parts changed are as follows:

<u>New Part Number</u>	<u>Cancelled Part No.</u>	<u>Nomenclature</u>	<u>Quantity Per Unit</u>
6768714	6757605	Hub, Converter Pump	1
6768707	6757621	Pump Assy., Oil	1
6768706	6757086	Gear and Body Assy.	1
6768704	6758349	Body, Pump	1

Spare Parts Information:

The new hub P/N 6768714 may be used for service on all units. The old hub P/N 6757605 may be used for service in units containing the old pump assembly. Service on the old hub will not be maintained.

The new gear and body assembly P/N 6768706 and the new pump assembly P/N 6768707 may be used for service in all units but must be used with the new converter hub. The old gear and body assembly P/N 6757086 and the old pump assembly P/N 6757621 may be used for service on all units with either the new or old hub. The old pump body, gear and body assembly and pump assembly will be maintained for service.

Service Manager - Transmissions

SPI 351
Page 1 of 7
Rev. "D" 11-19-65

Subject: Release of Greased Input Drive Configuration

Equipment Affected: TC-300 Converters

Effective Serial Numbers: S/N 23242 - TC-300

As a product improvement, a new input drive configuration has been released to TC-300 converters.

The new configuration, which was designed to decrease gear noise and extend gear life, incorporates a greased gear type drive. The grease is retained in the area between the flywheel and the converter drive cover by a seal which fits on the drive cover.

The newly released parts are as follows:

<u>Part Number</u>	<u>Part Name</u>	<u>Quantity</u>
6769876	Drive Ring	1
6769818	Sealring	1
9412270	Bolt	8
6769877	Grease	As Req. *
6769988	Gasket	1
103635	Nut	8
6769849	Cover Assy., Conv. Drive	1
6769913	Kit	1

* See Step 7, Page 4

SPI 351
 Page 2 of 7
 Rev. "D" 11-19-65

Installation of the new drive configuration in standard TC-300 converters which now have a gear type drive, will require the following changes:

<u>Add</u>	<u>Delete</u>	<u>Name</u>	<u>Quantity</u>
6769876	5192163	Drive Ring	1
6769818		Sealring	1
9412270	9409231	Bolt	8
6769877		Grease	As Req. *

TC-300 converters which have the front disconnect option, with the gear type drive, will require the parts listed above, plus the following:

<u>Add</u>	<u>Delete</u>	<u>Name</u>	<u>Quantity</u>
6769988		Gasket	1
102635	103026	Nut	8
	103321	Washer	8

Standard TC-300 converters with rollpin drive, will require the changes listed below:

<u>Add</u>	<u>Delete</u>	<u>Name</u>	<u>Quantity</u>
	6769070	Drive Ring Assy.	1
6769876		Drive Ring	1
6772408	6769071	Cover, Conv. Drive	1
6769818		Sealring	1
9412270	9409231	Bolt	8
6769877		Grease	As Req. *

* See Step 7, Page 4

SPI 351
 Page 3 of 7
 Rev. "D" 11-19-65

TC-300 converters which have the front disconnect option with rollpin drive, will require the same parts changes as standard TC-300 converters with rollpin drive, plus the following:

<u>Add</u>	<u>Delete</u>	<u>Name</u>	<u>Quantity</u>
6769988		Gasket	1
102635	103026	Nut	8
	103321	Washer	8

TC-376 converters, Assy. No. 6759643, will require the following parts changes:

<u>Add</u>	<u>Delete</u>	<u>Name</u>	<u>Quantity</u>
	6769070	Ring Assembly	1
6769876		Ring	1
6769849	6769049	Cover Assy., Converter Drive	1
6769818		Sealring	1
9412270	9409231	Bolt	8
6769877		Grease	As Req. *

The new drive ring P/N 6769876, seal P/N 6769818 and bolts P/N 9412270 are contained in a kit P/N 6769913. This kit will also include a container of grease P/N 6769877.

Since the grease used in this drive is the key factor in decreasing gear wear and gear noise, it is most important that the proper grade and type grease is used. Two readily available brands which are satisfactory are Mobil-Grease Special, with molybdenum disulfide, and Standard Calumet Viscous Lubricant 8X. Additional brands are listed on the attached supplement.

* See Step 7, Page 4

SPI 351
Page 4 of 7
Rev. "D" 11-19-65

The new parts may be installed as follows:

1. If the converter drive cover on the transmission or converter is a rollpin type cover, or if it is a badly worn gear type cover, it must be replaced by a new gear type cover P/N 6772408. (TC-376 converters, Assy. No. 6759643, require cover assembly P/N 6769849).
2. Remove the ring gear from the engine flywheel.
3. Drill one 1/8" vent hole in the engine flywheel or in the disconnect clutch drive plate. This should be located inside a 4" radius from the center of the flywheel, or, in converters with the front disconnect option, inside a radius of 2 1/2" from the center of the drive plate. Avoid drilling into the area which mates with the crankshaft flange.

Note: In some Detroit Diesel engines, there may already be a hole in the flywheel. If this engine is mated to a CRT-3000 series transmission or to a standard TC-300 converter, the hole should be plugged unless it is within a four inch radius from the center of the flywheel.

4. Apply a thin, even coat of #3 Permatex to the face of the ring gear and the mating surface on the flywheel. (In front disconnect models of TC-300 converters, apply the Permatex to both sides of gasket P/N 6769988.) Allow the Permatex to air dry for several minutes.
5. Bolt the ring gear P/N 6769876 to the flywheel (Standard Models) or to the clutch drive plate (Front Disconnect Models), using eight bolts P/N 9412270. (Front Disconnect Models will also require eight P/N 102635 nuts and one P/N 6769988 gasket.) Tighten the bolts to 36-43 lb.-ft. torque.
6. Apply a thin film of grease to the seal P/N 6769818 and install the seal in the groove behind the gear teeth in the converter drive cover.
7. Distribute enough grease P/N 6769877 around the inside of the drive ring to fill the spaces between the gear teeth and the cavity between the flywheel and the drive ring as shown by the cross-hatch area in attached sketches. The amount of grease used should be held to a minimum - approximately 1 1/2 ounces. Use grease only in the cross-hatched area shown.

Rev. "D"

SPI 351
Page 5 of 7
Rev. "D" 11-19-65

8. Mesh the gear on the drive cover with the drive ring gear, making sure the seal enters the I.D. of the drive ring.
9. Follow standard procedure in completing the installation.

Spare Parts Information:

All old parts in spare parts stock may be used for service on units which do not have the new drive configuration.

Explanation of Revision "C"

The method of installing input drive rings onto engine flywheels and disconnect clutch drive plates has been changed as shown below.

Old Method

1. Internal toothed lockwashers used with the drive ring bolts.
2. Drive ring bolts tightened to 33-40 ft. -lbs. torque.

New Method


1. No washers required.
2. Required torque value increased to 36-43 ft. -lbs.

It is very important that the new procedure be followed. The lockwashers, P/N 6769878 have been removed from drive ring kits and will no longer be shipped with transmissions. Lockwashers attached to transmissions or converters awaiting installation should be removed and discarded.

The new torque requirement on the drive ring bolts should be carefully observed.


Service Manager - Transmissions

SPI 351
Page 6 of 7
Rev. "D" 11-19-65



CONVERTER WITH FRONT DISCONNECT CLUTCH

SPI 351
Page 7 of 7
Rev. "D" 11-19-65



STANDARD CONVERTERS & CRT-3000 SERIES TRANSMISSIONS

SPI 499
Page 1 of 1
December 13, 1961

Subject: Changes in Turbine Shaft and Rear Bearing

Equipment Affected: TC-200 and TC-300 Series Converters
(Rear Disconnect Models only)

Effective Serial Numbers: TC-200 - S/N 32093
TC-300 - S/N 32587

Rear disconnect models of TC-200 and TC-300 Series converters include a single-row ball bearing which supports the output end of the turbine shaft. In order to prevent this bearing from turning on the shaft, the diameter of the journal on the shaft has been increased, thus providing a tighter fit between the bearing and the shaft.

A new bearing has been released for use with the heavier shaft. The new bearing is so designed that the tight fit of the bearing on the shaft will not affect the internal clearances in the bearing.

The part number changes are as follows:

<u>New Part Number</u>	<u>Old Part Number</u>	<u>Part Name</u>
907050	903307	Bearing, Rear
6772734	6759948	Shaft, Turbine (TC-300)
6772735	6758592	Shaft, Turbine (TC-200)

Effect on Interchangeability:

The new shafts P/N 6772734 and P/N 6772735 may be used for service on units, regardless of serial number, but require the use of the new bearing P/N 907050.

The new bearing may be used on both old and new shafts.

The old bearing, P/N 903307, must not be used with the new shafts.

Spare Parts Information:

All old shafts, P/N 6759948 and P/N 6758592, and the old bearings, P/N 903307, may be used for service in converters with serial numbers below S/N 32093 (TC-200) and S/N 32587 (TC-300).

Service Manager - Transmissions

Subject: Change In Stator Design

Equipment Affected: TC-200 Series Converters

Effective Serial Number: S/N 31823

For ease of manufacturing, the converter stator used in TC-200 series converters has been changed from a weldment to a die casting.

The change in the stator design made it necessary to redesign the various parts that mate with the stator.

The part number changes are as follows:

<u>New Part No.</u>	<u>Old Part No.</u>	<u>Part Name</u>
3777395	3702688	Stator
3735785		Washer, Thrust (2)
	3702103	Washer, Thrust (2)
	6756233	Washer, Thrust (1)
	3709094	Washer, Thrust (1)
		(In the old design, four thrust washers were used. The new design requires only two. See Explanation of Parts Changes on Page 2.)
3702744	6756629	Washer, Thrust, Converter Pump
6773200	6755266	Pump Assy., Charging Oil
6773199	6754964	Support, Stator (Groundsleeve)
	6769234	Stator Assy.
6774685		Kit, Stator Replacement (This kit can be used in all TC-200 series converters, regardless of serial number, therefore a service stator assembly is no longer required.)

Stator Replacement Kit

The Stator replacement kit, P/N 6774685, contains all the parts necessary for the replacement of the stator in all TC-200 converters, regardless of serial number. An instruction sheet (giving the recommended assembly procedure) is included in the kit. (A copy of the instruction sheet is attached to this letter.)

SPI 500
Page 2 of 3
Rev. "A" 1-16-63

The kit contains the following parts:

<u>Part Number</u>	<u>Part Name</u>	<u>Quantity</u>
3777395	Stator	1
3719260	Cam, Stator	1
3702104	Snapring, Thrust Washer Retaining	2
3735785	Washer, Stator Thrust	2
3702744	Washer, Converter Pump Thrust	1
6774686	Instruction Sheet No. 38	1

Explanation Of Parts Changes:

In the old configuration, a steel thrust washer, P/N 3702103, was installed on each side of the stator cam, and the cam and washers were retained in the stator by two snaprings. On the turbine side of the stator, an aluminum thrust washer, P/N 3709094, fitted into the stator, bearing against the steel thrust washer. A cast iron thrust washer, P/N 6756233, was similarly used on the converter pump side of the stator, however, this washer splined onto the stator support.

In the new configuration, only one thrust washer is used on each side of the stator cam. On the turbine side, washer P/N 3735785 replaces both the steel washer, P/N 3702103, and the aluminum washer, P/N 3709094. On the converter pump side of the stator, a second washer P/N 3735785 replaces both the steel washer P/N 3702103 and the cast iron thrust washer P/N 6756233. Thus, one part number, 3735785, replaces three part numbers - 3702103, 3709094 and 6756233.

The old converter pump thrust washer, P/N 6756629, had a bronze facing that mated with the cast iron thrust washer. Since the cast iron washer has been replaced by an aluminum washer, the bronze facing is no longer desirable. The bronze-faced washer was replaced by a plain steel converter pump thrust washer, P/N 3702744. NOTE: Under no circumstances should the bronze-faced thrust washer be interchanged with the plain steel thrust washer. An early failure will result.

The change in the stator support was brought about by the elimination of the splined thrust washer, P/N 6756233. Since the new thrust washer is not splined to the stator support, a much shorter spline on the support is required.

Affect On Parts Interchangeability:

The new stator, P/N 3777395, can be used in all TC-200 series converters, but requires the use of the new washers, P/N 3735785, and the new converter pump thrust washer, P/N 3702744.

The old stator, P/N 3702688, can not be used with any of the new parts.

The new thrust washers, P/N 3702744 and P/N 3735785 are for use with the new stator only.

SPI 500
Page 3 of 3
Rev. "A" 1-16-63

The new converter pump thrust washer, P/N 3702744, can be used with the new stator only. The old converter pump thrust washer, P/N 6756629, can be used with the old stator only.

The new stator support, P/N 6773199, and/or the new charging pump assembly, P/N 6773200, can be used with the new stator only.

The old stator support, P/N 6754964, can be used with both the new stator and the old stator.

Spare Parts Information:

All old parts in spare parts stock should be used in converters with serial numbers below S/N 31823.

The parts listed below will be maintained for service:


<u>Part No.</u>	<u>Part Name</u>
6756629	Washer, Thrust
6756233	Washer, Thrust
3709094	Washer, Thrust
6755266	Pump Assy.
6754964	Support, Stator
3702103	Washer, Thrust

Service Manager
Transmissions Operations

Instruction Sheet No. 38
(For Kit P/N 6774685)

PLEASE NOTE: If the serial number of the converter you are repairing is below S/N 3182, be sure to remove and discard the old converter pump thrust washer. It is a steel washer which has three tabs and a bronze facing. The new thrust washer, P/N 3702744, has the three tabs but does not have the bronze facing.

Warning - If the old bronze-faced washer is used with the parts in this kit, an early failure will result.



Assembly Procedure

1. Assemble the converter to the point where the converter pump (22) has been installed.
2. Install the new thrust washer (19) and the snapring (12).
3. Note the word "Front" cast on one side of the stator (9). Turn the stator over and install the thrust washer (13) and the snapring (14).
4. Install the cam (10) into the stator, from the front side. Be sure the deep end of the cam pockets are in a counterclockwise direction.
5. Install the rollers (15) and springs (16) into the cam pockets, positioning the springs so that the open ends will be next to the race (11).
6. Insert the race into the stator, then install the stator and race onto the stator support (groundsleeve). Work carefully to prevent the rollers and springs from dropping out of the stator.
7. Install the snapring (6) into the groove in the stator support.
8. Install the thrust washer (3) and the snapring (9) into the stator.

SEE INSIDE FRONT COVER BEFORE USING THIS INDEX

NUMERICAL PARTS INDEX

The numerical parts index lists the parts reference number and the figure number of the illustration in which it appears. The reference numbers are keyed to the group listings. However, you must know the converter assembly part number to identify the right group.

PART NO	FIG NO	REF NO	HISTORY	PART NO	FIG NO	REF NO	HISTORY
102635	6-1	9		179812	1-2	40	
103026	1-2	10		179812	3	56	
103026	6-1	9		179812	3-1	56	
103320	1	54		179812	3-2	50	
103320	1-1	59		179812	3-3	56	
103320	1-2	44		179817	1	53	
103320	3	40		179817	1-1	58	
103320	3-1	42		179817	1-2	43	
103320	3-2	36		179817	3	41	
103320	3-3	42		179817	3-1	43	
103320	7-1	8		179817	3-2	37	
103321			R 103323	179817	3-3	43	
103321	2	36		179819	7-1	7	
103321	4	5		179837	2	35	
103321	5-1	30		179837	4	6	
103321	5-1	35		179840	6-1	14	
103321	6-1	13		179841	5-1	29	
103323			RB 103321	179842			R 177845
103323	2	10		179842	5-1	36	
103323	4	43		179845			R 179887
105456	1	37		179887			RB 179845
105456	1-1	42		181345	5-1	24	
105456	1-2	27		181374			RB 9409038
105456	3	45		181429	2	11	
105456	3-1	47		181429	4	44	
105456	3-2	41		186271	7-1	1	
105456	3-3	47		191758			R 127800
111296			RB 127800	191758	5-1	25	
113782	5-1	32		191758	6-1	7	
113903	6-1	6		214279	5-1	23	
113989			R 6754527	436569			RB 6756618
113989	3	37		442812			RB 451006
113989	3-1	39		444576	1	46	
113989	3-2	33		444576	1-1	49	
113989	3-3	39		444576	1-2	36	
113998	1	55		444576	3	54	
113998	1-1	60		444576	3-1	54	
113998	1-2	45		444576	3-2	48	
113998	3	39		444576	3-3	54	
113998	3-1	41		444576	7-1	19	
113998	3-2	35		444672	1	41	
113998	3-3	41		444672	1-1	48	
114351	5-1	11		444672	1-2	31	
114498	5-1	26		444672	3	47	
114604	5-1	10		444672	3-1	49	
117213	1-2	1		444672	3-2	43	
127800			R 111296	444672	3-3	49	
127800			RB 191758	444678	1	49	
142862	1	44		444678	1-1	45	
142862	1-1	51		444678	1-2	39	
142862	1-2	34		444678	3	57	
142862	3	53		444678	3-1	57	
142862	3-1	53		444678	3-2	51	
142862	3-2	47		444678	3-3	57	
142862	3-3	53		451006			R 442812
147465	7-1	16		451006	1	1	
177845			RB 179842	451006	1-1	7	
179793	3	21		451006	3	4	
179812	1	50		451006	3-1	10	
179812	1-1	55		451006	3-2	4	

R - REPLACES

RB - REPLACED BY

PART NO	FIG NO	REF NO	HISTORY	PART NO	FIG NO	REF NO	HISTORY
451006	3-2	59		3689838	4	15	
451006	3-3	10		3691806	1	17	
453621	1	47		3691806	1-1	22	
453621	1-1	47		3702068			RB 760612
453621	1-2	37		3702069	1	27	
453621	3	59		3702069	1-1	32	
453621	3-1	59		3702069	1-2	17	
453621	3-2	53		3702079			RB 3790478
453621	3-3	59		3702082			RB 3713622
456635	2	12		3702099			RB 3719260
456635	4	16		3702100			RB 3702103
753859			RB 6778856	3702101	1	15	
753860			RB 6778857	3702101	1-1	20	
760612			R 3702068	3702103			R 3702107
760612			RB 3737894	3702103	1	62	
900454			R 954551	3702103	1-1	67	
900454			RB 907540	3702104	1	7	
903010	3-1	5		3702104	1	14	
903010	3-2	6		3702104	1	60	
903010	3-3	5		3702104	1-1	12	
903011	3	9		3702104	1-1	19	
903202			R 954498	3702104	1-1	65	
903202			RB 907411	3702688			RB 3796309
903208	1-1	5		3702718			RB 3719262
903208	3	9		3702724	1	5	
903209			RB 6757374	3702744			R 6756629
903307			RB 907050	3702744	1	19	
903307	2	4		3702744	1-1	25	
907050			R 903307	3709094	1	56	
907050	2	4		3709094	1-1	61	
907050	2	4		3713622			R 3702082
907050	4	2		3713622	1	20	
907411			R 903202	3713622	1-1	24	
907411	2	24		3717166	1	21	
907411	4	30		3717166	1-1	26	
907540			R 900454	3719252	1	29	
907540	6-1	3		3719252	1-1	34	
954466	3	22		3719252	1-2	19	
954498			RB 903202	3719260			R 3702099
954528	4	2		3719260	1	10	
954551			RB 900454	3719260	1	63	
2222424	2	22		3719260	1-1	15	
2222424	2	31		3719260	1-1	68	
2222424	2	34		3719261	1	16	
2222424	4	28		3719261	1-1	21	
2222424	4	37		3719262			R 3702718
3224085	2	25		3719262	1	4	
3224085	4	31		3735785	1	8	
3224773	2	27		3735785	1	13	
3224773	4	33		3735785	1-1	13	
3324773	4	33		3735785	1-1	18	
3689751	1	18		3737894			R 760612
3689751	1-1	23		3737894			RB 3772748
3689760	1	30		3744348	1	26	
3689760	1-1	35		3744348	1-1	31	
3689760	1-2	20		3744348	1-2	16	
3689826	1	31		3744349	1	28	
3689826	1-1	36		3744349	1-1	33	
3689826	1-2	21		3744349	1-2	18	
3689838	2	2		3772748			R 3737894

R - REPLACES

RB - REPLACED BY

PART NO	FIG NO	REF NO	HISTORY	PART NO	FIG NO	REF NO	HISTORY
3772748	1	25		6750127	1-1	4	
3772748	1-1	30		6750272			RB 6768257
3772748	1-2	15		6751524	2	26	
3777395	1	9		6751524	4	32	
3777395	1-1	14		6751531	2	14	
3790478			R 3702079	6751531	4	18	
3790478	1	3		6751541			RB 9422228
3796309			R 3702688	6751822			R 7709143
3796309	1	61		6751822	6-1	1	
3796309	1-1	66		6751839	4	12	
5192142	5-1	15		6751839	4	15	
5192153	5-1	2		6752033	7-1	9	
5192176	5-1	18		6752034	7-1	11	
5192180	5-1	1		6752035	7-1	10	
5192180	6-1	11		6753487	6-1	2	
5192182	5-1	7		6753849			RB 6758213
5192489	5-1	28		6753857			RB 6773249
5193064	5-1	27		6753866	3	26	
5193253			RB 5194671	6753866	3-1	28	
5193255	5-1	31		6753866	3-2	22	
5193258	5-1	5		6753866	3-3	28	
5193259	5-1	20		6753966	2	5	
5193260			RB 5196719	6753966	4	4	
5193420	5-1	19		6754299	7-1	3	
5193421	5-1	17		6754314	7-1	5	
5193422	5-1	13		6754349	2	40	
5193430	5-1	12		6754349	4	8	
5193431	5-1	6		6754488	3	24	
5194138	5-1	14		6754488	3-1	26	
5194140	5-1	16		6754488	3-2	21	
5194244	5-1	33		6754488	3-3	27	
5194291	5-1	9		6754489			RB 6757729
5194294	5-1	8		6754490	1	51	
5194365	5-1	4		6754490	1-1	56	
5194671			R 5193253	6754490	1-2	41	
5194671	5-1	3		6754490	3	43	
5196719			R 5193260	6754490	3-1	45	
5196719	5-1	21		6754490	3-2	39	
6700296	4	47		6754490	3-3	45	
6701230	1	38		6754495	1	52	
6701230	1-1	43		6754495	1-1	57	
6701230	1-2	28		6754495	1-2	42	
6701230	3	44		6754495	3	42	
6701230	3-1	46		6754495	3-1	44	
6701230	3-2	40		6754495	3-2	38	
6701230	3-3	46		6754495	3-3	44	
6702958	3	35		6754501			RB 6759946
6702958	3-1	37		6754505			RB 6757783
6702958	3-2	31		6754506	2	17	
6702958	3-3	37		6754506	4	22	
6702989	3-1	4		6754508	2	16	
6702989	3-3	4		6754508	4	21	
6703023	4	1		6754519			RB 6757605
6703224			RB 6758296	6754527			RB 113989
6750046	1	6		6754528			RB 6757599
6750046	1	12		6754549			RB 6758599
6750046	1-1	11		6754549			RB 6768955
6750046	1-1	17		6754550			RB 6757621
6750046	2	3		6754922	3	6	
6750046	4	1		6754947	4	10	

R - REPLACES

RB - REPLACED BY

PART NO	FIG NO	REF NO	HISTORY	PART NO	FIG NO	REF NO	HISTORY
6754958	1	11		6755903	4	13	
6754958	1-1	16		6755988	3	28	
6754962			R 6754962	6755988	3-1	30	
6754962			RB 6754962	6755988	3-2	24	
6754962	2	1		6755988	3-3	30	
6754963	2	9		6755999			RB 6756847
6754968	1	33		6756001	3	27	
6754968	1-1	38		6756001	3-1	29	
6754968	1-2	23		6756119	7-1	17	
6754994	3	14		6756233	1	57	
6754994	3-1	17		6756233	1-1	62	
6754999			RB 6771296	6756321	2	32	
6755004	3	7		6756348			RB 6774572
6755031	4	17		6756362	7-1	12	
6755032	2	13		6756519	1	22	
6755221	1	2		6756519	1-1	27	
6755271			RB 6769234	6756615	6-1	8	
6755302	2	6		6756616			RB 6772307
6755302	4	41		6756618			R 436569
6755325			RB 6757712	6756618	6-1	5	
6755325	3	5		6756620	6-1	4	
6755333	4	42		6756627	6-1	4	
6755372			RB 6759947	6756629			RB 3702744
6755377	2	21		6756629	1	58	
6755377	4	27		6756629	1-1	63	
6755380	4	35		6756637			RB 6778121
6755383	2	19		6756644	1	24	
6755463			RB 6758284	6756644	1-1	29	
6755464			RB 6768902	6756644	1-2	14	
6755467			RB 6757713	6756658	7-1	6	
6755469	2	39		6756659	3	62	
6755488	7-1	2		6756659	3-2	54	
6755618	2	23		6756659	7-1	6	
6755618	4	29		6756689	2	29	
6755619	2	20		6756689	4	38	
6755619	4	34		6756691	4	39	
6755786	1	35		6756693	1	45	
6755786	1-1	40		6756693	1-1	50	
6755786	1-2	25		6756693	1-2	35	
6755786	3	38		6756693	3	51	
6755786	3-1	40		6756693	3-1	51	
6755786	3-2	34		6756693	3-2	45	
6755786	3-3	40		6756693	3-3	51	
6755789	1	40		6756706	2	30	
6755789	1-1	54		6756706	4	36	
6755789	1-2	30		6756847			R 6755999
6755789	3	55		6756847	3	27	
6755789	3-1	55		6756847	3-1	29	
6755789	3-2	49		6756856	2	18	
6755789	3-3	55		6756864	7-1	15	
6755803			RB 6757634	6756865	4	25	
6755838			RB 6769091	6756869	4	17	
6755892	3	16		6756872	1	34	
6755892	3-1	19		6756872	1-1	39	
6755892	3-3	19		6756872	1-2	24	
6755896	3	19		6756913	2	40	
6755897	3	17		6756913	4	8	
6755897	3-1	20		6756946	4	26	
6755897	3-2	13		6756947	4	24	
6755903			R 6770239	6756947	7-1	14	

R - REPLACES

RB - REPLACED BY

PART NO	FIG NO	REF NO	HISTORY	PART NO	FIG NO	REF NO	HISTORY
6757086			RB 6768706	6759930			RB 6772312
6757374			R 903209	6759932	1-1	10	
6757374			RB 9411628	6759946			R 6754501
6757426	2	37		6759946	4	14	
6757426	4	7		6759947			R 6755372
6757521	2	33		6759947	4	14	
6757599			R 6754528	6759948			R 6757783
6757599			RB 6769530	6759948			RB 6772734
6757605			R 6754519	6759971	3-2	20	
6757605			RB 6768714	6759971	3-3	26	
6757621			R 6754550	6763013			R 7374627
6757621			RB 6768707	6763013	4	3	
6757634			R 6755803	6763013	4	3	
6757634	3	20		6763013	4	19	
6757634	3-1	22		6764025	4	46	
6757709	1	48		6764626			R 6769530
6757709	1-1	46		6764626	3-3	38	
6757709	1-2	38		6768267			R 6750272
6757712			R 6755325	6768267			RB 6832907
6757712			RB 6772408	6768267			RB 6832907
6757713			R 6755467	6768267	3	52	
6757713			RB 6769453	6768346	4	40	
6757729			R 6754489	6768350	3	34	
6757729			RB 6768942	6768350	3-1	36	
6757737	2	41		6768350	3-2	30	
6757737	4	50		6768350	3-3	36	
6757757	2	42		6768351	3	33	
6757758	4	45		6768351	3-1	35	
6757783			R 6754505	6768351	3-2	29	
6757783			RB 6759948	6768351	3-3	35	
6758054	4	26		6768425	2	23	
6758124	2	19		6768425	4	29	
6758213			R 6753849	6768426	2	20	
6758213			RB 6768644	6768426	4	34	
6758284			R 6755463	6768644			R 6758213
6758284			RB 6768903	6768644			RB 6769816
6758295	2	28		6768704	3	32	
6758296			R 6703224	6768704	3-1	34	
6758296	3	25		6768704	3-2	28	
6758296	3-1	27		6768704	3-3	34	
6758592			RB 6772735	6768706			R 6757086
6758597	3	58		6768706	3	30	
6758597	3-1	58		6768706	3-1	32	
6758597	3-2	52		6768706	3-2	26	
6758597	3-3	58		6768706	3-3	32	
6758599			R 6754549	6768707			R 6757621
6758599			RB 6768956	6768707	3	29	
6758777	3	17		6768707	3-1	31	
6758987			RB 6772328	6768714			R 6757605
6758987	6-1	8		6768714	3	23	
6758988	6-1	8		6768714	3-1	25	
6759462	2	1		6768727	3	11	
6759906	1-1	3		6768902			R 6755464
6759906	3-1	3		6768902	3	15	
6759906	3-3	3		6768902	3-1	18	
6759926	1-1	1		6768903			R 6758284
6759926	3-1	1		6768903	3	11	
6759926	3-3	1		6768903	3-1	14	
6759927	1-1	6		6768942			R 6757729
6759928	1-1	8		6768942	1	42	

R - REPLACES

RB - REPLACED BY

ALLISON TORQMATIC CONVERTER SERIES 200-300 PARTS CATALOG

INDEX 7

PART NO	FIG NO	REF NO	HISTORY	PART NO	FIG NO	REF NO	HISTORY
6768942	1-1	53		6769816			R 6768644
6768942	1-2	32		6769816	3	31	
6768942	3	49		6769816	3-1	33	
6768942	3-1	50		6769816	3-2	27	
6768942	3-2	44		6769816	3-3	33	
6768942	3-3	50		6769818	3	3	
6768955			R 6754549	6769818	3-1	9	
6768955	1	39		6769818	3-2	3	
6768955	1-1	44		6769818	3-3	9	
6768955	1-2	29		6769849			R 6769049
6768956			R 6758599	6769849	3	60	
6768956	3	46		6769856			R 6769091
6768956	3-1	48		6769856	3	18	
6768956	3-2	42		6769856	3-1	21	
6768956	3-3	48		6769876			RB 6775414
6769044			RB 6769623	6769908	2	19	
6769045	3	18		6769988	6-1	12	
6769048	3	16		6770239			R 8347316
6769049			RB 6769849	6770239			RB 6755903
6769050	4	49		6771296			R 6754999
6769051	4	48		6771296	3	13	
6769052	3	50		6771296	3-1	16	
6769053	3	63		6772301	3-1	11	
6769054	3	49		6772301	3-3	11	
6769055	3	36		6772307			R 6756616
6769057	4	41		6772307	6-1	8	
6769060	3	10		6772309	3-1	6	
6769061	3	29		6772309	3-3	6	
6769062	3	23		6772310	3-1	13	
6769073	3	48		6772312			R 6759930
6769089			RB 6769622	6772312	1-1	2	
6769090			RB 6769621	6772312	3-1	2	
6769090	3	38		6772312	3-3	2	
6769091			R 6755838	6772328			R 6758987
6769091			RB 6769856	6772328	6-1	8	
6769105	3	11		6772408			R 6757712
6769234			R 6755271	6772408			RB 6830464
6769234	1	59		6772408	3	8	
6769234	1-1	64		6772734			R 6759948
6769453			R 6757713	6772734	4	11	
6769453	3	10		6772735			R 6758592
6769491	3-2	17		6772735	2	39	
6769491	3-3	21		6772735	2	39	
6769530			R 6757599	6772786	2	19	
6769530			RB 6764626	6773199	1	32	
6769530	3	36		6773199	1-1	37	
6769530	3-1	38		6773200	1	23	
6769621			R 6769090	6773200	1-1	28	
6769621	3	38		6773249			R 6753857
6769621	3	38		6773249	2	8	
6769621	3-1	40		6773249	4	10	
6769621	3-2	34		6773679	3-2	15	
6769622			R 6769089	6773679	3-3	22	
6769622	3	55		6773933	4	41	
6769622	3	55		6774008	3-2	60	
6769622	3-1	55		6774012	1-2	2	
6769622	3-2	49		6774012	3-2	56	
6769623			R 6769044	6774104	1-2	22	
6769623	3	46		6774105	1-2	12	
6769631	3-2	16		6774109			RB 6778111

R - REPLACES

RB - REPLACED BY

PART NO	FIG NO	REF NO	HISTORY	PART NO	FIG NO	REF NO	HISTORY
6774266	3	46		6778857	4	20	
6774266	3-2	42		6779631	3-3	23	
6774572			R 6756348	6830464			R 6772408
6774572	3	61		6830464	3-2	5	
6774616	3-2	23		6831578	4	8	
6774616	3-3	29		6832907			R 6768267
6774620	3-2	14		6832907			R 6768267
6774620	3-3	20		6832907	1	43	
6774621	3-2	19		6832907	1-1	52	
6774621	3-3	25		6832907	1-2	33	
6774622	3-2	7		6832907	3-1	52	
6774626	3-2	32		6832907	3-2	46	
6774627	3-2	23		6832907	3-3	52	
6774627	3-3	29		7374627			RB 6763013
6774794	3-2	25		7450737			R 8347400
6774794	3-3	31		7450737	3	12	
6774816	3-3	13		7450737	3-1	15	
6774847	3-2	12		7709143			RB 6751822
6774847	3-3	18		8347316			RB 6770239
6774962	3-2	8		8347400			RB 7450737
6774962	3-3	14		8522609	7-1	4	
6774966	3-2	11		8618363	1-1	9	
6774966	3-3	17		8618363	3-1	12	
6774968	3-2	10		8618363	3-3	12	
6774968	3-3	16		9409033	1-2	5	
6775414			R 6769876	9409038			R 181374
6775414	3	1		9409038	6-1	10	
6775414	3-1	7		9409055			RB 9409203
6775414	3-2	1		9409055	2	7	
6775414	3-3	7		9409060	7-1	18	
6776818	3-2	7		9409062	1	36	
6777106	1-2	13		9409062	1-1	41	
6777107	1-2	9		9409062	1-2	26	
6777108			R 6777460	9409073			RB 9409088
6777108			RB 6777884	9409088			R 9409073
6777108	1-2	6		9409088	3	21	
6777109	1-2	8		9409088	3-1	23	
6777110			R 6777459	9409203			R 9409055
6777110			RB 6777885	9409203			RB 9409240
6777110	1-2	7		9409203	2	7	
6777120	4	8		9409203	2	7	
6777448	1-2	3		9409203	2	38	
6777448	3-2	57		9409203	4	9	
6777449	1-2	4		9409203	4	23	
6777449	3-2	58		9409227	4	23	
6777459			RB 6777110	9409227	7-1	13	
6777460			RB 6777108	9409240			R 9409203
6777884			R 6777108	9409240	2	7	
6777884	1-2	6		9409240	2	7	
6777885			R 6777110	9409240	4	9	
6777885	1-2	7		9409258	3-2	55	
6778111			R 6774109	9411628			R 6757374
6778111	1-2	11		9411628			RB 9417910
6778121			R 6756637	9412270	3	2	
6778121	5-1	34		9412270	3-1	8	
6778856			R 753859	9412270	3-2	2	
6778856	2	15		9412270	3-3	8	
6778856	4	20		9417499	3-2	9	
6778857			R 753860	9417499	3-3	15	
6778857	2	15		9417910			R 9411628

R - REPLACES


RB - REPLACED BY

ALLISON TORQMATIC CONVERTER SERIES 200-300 PARTS CATALOG


INDEX 9

PART NO	FIG NO	REF NO	HISTORY	PART NO	FIG NO	REF NO	HISTORY
9417910	3	22					
9417910	3-1	24					
9420046	3-2	18					
9420046	3-3	24					
9422228			R 6751541				
9422228	2	12					
9422228	4	16					

R - REPLACES



Model TC 250 converter—cross-section view



Model TC 300 converter (3-element)—cross-section view

QUICK REFERENCE LISTING
FOR YOUR TORQMATIC DRIVE

Fill In Now

ALLISON TORQMATIC TRANSMISSION

1. Model No. _____ Assy Part No. _____
Serial No. _____ Installation _____

ALLISON TORQMATIC TRANSMISSION

2. Model No. _____ Assy Part No. _____
Serial No. _____ Installation _____

ALLISON TORQMATIC TRANSMISSION

3. Model No. _____ Assy Part No. _____
Serial No. _____ Installation _____

ALLISON TORQMATIC TRANSMISSION

4. Model No. _____ Assy Part No. _____
Serial No. _____ Installation _____

ALLISON TORQMATIC TRANSMISSION

5. Model No. _____ Assy Part No. _____
Serial No. _____ Installation _____

ALLISON TORQMATIC TRANSMISSION

6. Model No. _____ Assy Part No. _____
Serial No. _____ Installation _____

ALLISON TORQMATIC TRANSMISSION

7. Model No. _____ Assy Part No. _____
Serial No. _____ Installation _____

ALLISON TORQMATIC TRANSMISSION

8. Model No. _____ Assy Part No. _____
Serial No. _____ Installation _____

ALLISON TORQMATIC TRANSMISSION

9. Model No. _____ Assy Part No. _____
Serial No. _____ Installation _____